

SONIFEX

RB-PD2
Stereo Profanity Delay

2016
Catalogue





RB-PD2 Stereo Profanity Delay



Category: Synchronisers, Delays & Silence Detectors.

Product Function: To introduce an audio delay into a program output allowing unsuitable or profane program material to be removed instantly.

Typical Applications: Radio and TV phone in programs and chat shows where content needs to be censored.

Features: Both analogue and digital audio I/O, automatic audio stretch algorithm allows seamless building of the delay, no pitch changes, up to 55 seconds of delay, Drop and Dump buttons, Dump via jingle playout or dropping of audio, GPI control of buttons, GPIO can follow current delay time.

The RB-PD2 is a stereo audio profanity delay used for live broadcast programs to prevent unwanted or obscene material from being transmitted. It features an automatic audio stretch algorithm that allows between 2 and 55 (*) seconds of delay to be built up live whilst "on air", whilst maintaining the correct pitch. The delay can also be acquired whilst playing a pre-selected audio file on a Compact Flash™ memory card. When the program is complete, the audio stretch algorithm seamlessly reduces the delay to zero.

The RB-PD2 has both balanced analogue and AES/EBU digital audio inputs and outputs on 3 pin XLR connectors and provides sample rates up to 48kHz at 24 bit. It can act as a combined A/D and D/A unit meaning that analogue inputs can be output as AES/EBU or vice-versa.

The delay can be initiated by pressing the BUILD DELAY button on the front panel. A front panel display shows the amount of delay being built-up, up to the amount initially selected.

There are several ways to make sure that any unwanted material is removed from the audio at the outputs. A COUGH function, activated from a dedicated front panel button, allows locally generated sounds being presented at the inputs, such as the presenter coughing or equipment switching noises, to be discarded.

The DUMP function, which is also activated from a front panel button, has 2 different modes. The first DUMP mode removes a section of audio that has already been buffered, by a pre-selected amount. The second DUMP mode plays a pre-selected audio file on the Compact Flash™ memory card. When the file has finished playing, the delay is then equal to the duration of the file. The DUMP button can be used multiple times to use up the built-up delay and once used, the unit automatically starts to rebuild the original delay time.

As a last resort, all the buffered audio can be discarded by pressing and holding the DUMP button which activates the DROP function.

At the end of a radio show when you want to broadcast live, the delay can be ramped down by pressing the front panel EXIT DELAY button.

A dedicated record mode allows audio presented at either the analogue or digital inputs to be recorded to a linear WAV file on a Compact Flash™ memory card. Additionally, the card format used is PC readable, allowing pre-recorded linear WAV

files to be transferred easily from a PC or other such device.

A front panel blue vacuum fluorescent display with rotary controller is used for selecting the various settings of the profanity delay, which include the start delay and dump modes, safe period, source (analogue or digital), sample rate and sample bit width as well as the required delay time. The current delay value, in seconds, is permanently displayed as is the current status of the unit. Additionally, input peak digits can be selected from +12dBu, +18dBu and +24dBu for FSD and two left and right pre-set potentiometers on the rear panel allow the input gain range to be altered by ±3dB around the selected peak digits. The analogue output gain range can be altered in software from -6dBu to +24dBu output level, ref FSD. Both analogue and digital outputs can be separately muted and a front panel Bypass button disengages electro-mechanical relays to divert both analogue and digital inputs to their outputs. This is also disengaged automatically when a power-fail occurs.

The RB-PD2 features a remote port supplying 8 inputs and 6 outputs, all of which are freely assignable. The inputs can be used to trigger any of the unit's functions such as build delay, activate cough or enter record mode and start a new recording. The outputs can provide external signalling to indicate when certain events have occurred such as the delay reaching the required value or the outputs being muted. Also,

the 6 remote outputs can optionally be made to follow 6 of the inputs with the current programme delay inserted between actuation on the input and actuation on the output. This can be useful for timed events that need to account for the delay built up by the RB-PD2.

Because playback from a Compact Flash™ card can be triggered remotely, the RB-PD2 can also be used at transmitter sites to play an emergency audio file via GPI in the event of silence detection.

The front panel EBU controls can be locked-out for situations where remote control is being used to run the unit, or where physical security is required.

A red LED indicates when power to the RB-PD2 is on.

* At 32kHz 16bit

Specification For RB-PD2

A/D Specification	
Maximum Input Level:	+28dBu
Input Impedance:	> 10kΩ bridging
Analogue & Digital Levels:	Selectable +12dBu, +18dBu, Input +24dBu for FSD
Analogue Pre-set Input Gain Range:	Adjustable 3dB loss to 3dB gain (L & R adjust)
Signal to Noise:	Better than -101dBFS (RMS A-weighted at 24bit)
Dynamic Range:	> 110dB
Distortion & Noise:	> 96dB THD + N at 1kHz
D/A Specification	
Maximum Output Level:	+24dBu
Output Impedance:	< 50Ω
Dynamic Range:	> 100dB
Analogue Output Gain Range:	Selectable -6dBu to +24dBu output level, ref FSD

Sampling Frequency:	Selectable 32kHz, 44.1kHz or 48kHz
Sample Width:	Selectable 16bit or 24bit
Channels:	Stereo
Minimum Delay:	2 seconds
Maximum Delay:	Dependent on sample and bit rates selected: 32kHz: 16 bit - 55 seconds 24 bit - 27.5 seconds 44.1kHz: 16 bit - 40 seconds 24 bit - 20 seconds 48kHz: 16 bit - 37 seconds 24 bit - 18.5 seconds

Rear Panel Connections	
Analogue Inputs:	2 x XLR 3 pin female (balanced) (L & R)
Analogue Outputs:	2 x XLR 3 pin male (balanced) (L & R)
Digital Inputs:	1 x AES/EBU XLR 3 pin female
Digital Outputs:	1 x AES/EBU XLR 3 pin male
Remote I/O Port:	15-way 'D'-type plug, 8 GPI inputs, 6 GPI outputs
Serial Comms Port:	9-way 'D'-type plug
Mains Input:	Filtered IEC, continuously rated 85 - 264VAC, 47 - 63Hz, fused, 60W peak, 30W average
Fuse Rating:	Anti-surge fuse 2A 20 x 5mm

Front Panel Controls	
Display:	Vacuum fluorescent display
Direct Control Push-Buttons:	Build Delay, Exit Delay, Cough, Audio Bypass & Dump/Drop
System Navigation:	Rotary selector with integral push-switch
Removable Audio Storage Device:	Compact Flash™ memory card port (supporting up to 2GB) CF™ card used must be PIO type 4 or higher

Equipment Type	
RB-PD2:	Stereo profanity delay
Physical Specification	
Dimensions (Raw):	48cm (W) x 15.8cm (D*) x 4.3cm (H) (1U) 19" (W) x 6.2" (D*) x 1.7" (H)(1U)
Dimensions (Boxed):	59cm (W) x 27.5cm (D*) x 11cm (H) 23.2" (W) x 10.8" (D*) x 4.3" (H)
Weight :	Nett: 1.7kg Gross: 2.3kg Nett: 3.7lbs Gross: 5lbs

* Note that this product is deeper than standard Redboxes

SONIFEX

www.sonifex.co.uk

UK Office:

Sonifex Ltd

61 Station Road, Irthlingborough,

Northants, NN9 5QE, UK

Tel: +44 (0) 1933 650700

Fax: +44 (0) 1933 650726

Email: sales@sonifex.co.uk

Australian Office:

Sonifex Pty Ltd

12/6 Leighton Place,

Hornsby NSW 2077, Australia

Tel: +61 (2) 9987 0499

Fax: +61 (2) 9476 4950

Email: sales@sonifex.com.au