

SONIFEX

CM-TBU

Line Powered Telephone Balance Unit

Catalogue





CM-TBU Line Powered Telephone Balance Unit



The CM-TBU line-powered telephone balance unit is compatible with all analogue direct exchange lines and provides a 4-wire communications system to interface with the telephone network.

The high degree of separation between send and receive signals makes it suitable for use in telephone IFB (interrupted foldback) applications and the high drive capacity at the 4-wire output enables a presenter's earpiece to be connected directly to the unit without an external amplifier.

This extremely compact unit is powered from the telephone line and provides an interface to a 4-wire circuit with separate level control of send and receive signals. Optimum rejection of the input signal on the

4-wire output is achieved in a bridge circuit by adjusting three elements (NULL, R-BAL and C-BAL) via potentiometers which simulate the complex line impedance. This can be used to compensate for local line variations or to adapt to the telephone systems of other countries, where line characteristics may differ. Optimization of the sidetone rejection does not involve the use of any test equipment and can be easily carried out while the system is in use.

Although the signal level being sent to the line can be manually adjusted using the 'SEND LEVEL' control over a wide range, the level control is followed by a limiter that prevents the telephone line signal level becoming overloaded or distorted. The limiter drives a



Category: Line Powered Telephone Hybrids.

Product Function: Provides separation between send and receive signals on an analogue telephone network and provides professional level balanced input & output signals.

Typical Applications: Talkback applications, e.g. to get cue feed to a remote presenter from a distant studio, hospital/community radio talkshows, house of worship remote listen & contribution to service.

Features:

- Isolated, full-duplex 4-wire interface to

direct non-digital telephone exchange lines.

- Line powered, requiring no battery or external power.
- Simple optimization of sidetone rejection with any country's telephone system.
- LEDs indicating 'Ring', 'Line Hold' and 'Limit' conditions.
- Input level control with line-sensing limiter and limit indicator.
- High drive output with level control for direct feed to presenter's earpiece, etc.
- Loop-through RJ11 line sockets provide universal connection to line and telephone set.
- Connection to the telephone set is maintained while the unit is in use.
- Small, rugged aluminium case.

'LIMIT' LED to indicate the onset of limiting.

Although the output stage can drive a presenter's earpiece in a telephone IFB application, the 'RECEIVE LEVEL' control may not be accessible to the presenter, who is normally situated some distance from the unit. The presenter may then require a local control of the earpiece signal level. The CM-TBU can be used to supply the correct signal level to a suitable battery powered earpiece belt-pack unit.

To enable communication between the 4-wire circuit and the telephone network, once the 4-wire and telephone line cable connections are made to the unit, the 'LINE CONNECT' switch can be pressed to power the unit from the line. This is indicated

by the 'ON' LED, and can either be done after an outgoing call has been dialled on a telephone set connected to the unit, or to answer an incoming call after the 'RING' LED is seen to flash. Note that a telephone set is not required for incoming calls unless an audible ring is required. If the sidetone level at the 4-wire output is found to be excessive, the outgoing signal level can be reduced using the 'SEND LEVEL' control or the balance controls can be adjusted to minimize it.

The unit is supplied with a connector and cable kit that enables connections to be made to both UK Telecom or the universal RJ11 sockets used in most telephone networks around the world.



Specification For CM-TBU

4-Wire Input

Input Impedance:	10k Ω , transformer coupled
Input Connector:	3 pin XLR female connector
Input Level Range:	-12dBu to +4dBu before limiting when connected to an average line

4-Wire Output

Output Impedance:	150 Ω , transformer coupled
Output Connector:	3 pin XLR male connector
Output Level Range:	-6dBu to +6dBu, for average line level
Sidetone Rejection:	30dB to 40dB average, depending on line characteristics

2-Wire Off Hook Voltage:

6V minimum

2 Wire Connectors:	RJ11 socket - line RJ11 socket - handset
--------------------	---

Front Panel Operational Controls

Line Connect:	Push button with indicator
Send Level:	Small rotary control
Receive Level:	Large rotary control
Null Balance:	Recessed preset potentiometer
R Balance:	Recessed preset potentiometer
C Balance:	Recessed preset potentiometer
Ring LED:	Indicates incoming ringing
Limit LED:	Indicates limiter active
On LED:	Indicates connection to the telephone line

Equipment Type

CM-TBU	Line powered telephone balance unit
--------	-------------------------------------

Physical Specification

Dimensions (Raw):	7.7cm (W) x 8.3cm (D) x 4.2cm (H) 3.0" (W) x 3.3" (D) x 1.7" (H)
Dimensions (Boxed):	22.9cm (W) x 12.7cm (D) x 7.6cm (H) 9.0" (W) x 5.0" (D) x 3.0" (H)
Weight:	Nett: 0.25kg Gross: 0.75kg Nett: 0.60lbs Gross: 1.7lbs

SONIFEX

www.sonifex.co.uk

UK Office:

Sonifex Ltd

61 Station Road, Irthlingborough,

Northants, NN9 5QE, UK

Tel: +44 (0) 1933 650700

Fax: +44 (0) 1933 650726

Email: sales@sonifex.co.uk

Australian Office:

Sonifex Pty Ltd

12/6 Leighton Place,

Hornsby NSW 2077, Australia

Tel: +61 (2) 9987 0499

Fax: +61 (2) 9476 4950

Email: sales@sonifex.com.au